

# Quantum Logical Gate Based on Fock Space

Wolfgang Freudenberg\*, Masanori Ohya† and Noboru Watanabe†

†Department of Information Sciences,  
Science University of Tokyo

Noda City, Chiba 278-8510, Japan

Tel: 0471-24-1501 (Ext. 3319), Fax: 0471-24-1532

E-mail :watanabe@is.noda.sut.ac.jp

\*Brandenburgische Technische Universität Cottbus,  
Fakultät 1, Institut für Mathematik, PF 101344, D-03013 Cottbus,  
Germany

## Abstracts:

In usual computer, there exists a restriction of computational speed because of irreversibility of logical gate. In order to avoid this demerit, Fredkin and Toffoli [3] proposed a conservative logical gate. Based on their work, Milburn [4] introduced a physical model of reversible quantum logical gate using beam splittings and a Kerr medium. This model is called FTM (Fredkin - Toffoli - Milburn gate). FTM gate was described by the quantum channel and the efficiency of information transmission of the FTM gate was discussed in [10]. FTM gate is using a photon number state as an input state for control gate. The photon number state might be difficult to realize physically. In this paper, we introduced a new unitary operator related to the Kerr device on symmetric Fock space in order to avoid this difficulty.

**Key words:** quantum logical gate, channels, beam splittings, FTM gate, Fock space

## 1. Quantum channels

Let  $(\mathbf{B}(\mathcal{H}_1), \mathfrak{S}(\mathcal{H}_1))$  and  $(\mathbf{B}(\mathcal{H}_2), \mathfrak{S}(\mathcal{H}_2))$  be input and output systems, respectively, where  $\mathbf{B}(\mathcal{H}_k)$  is the set of all bounded linear operators on a separable Hilbert space  $\mathcal{H}_k$  and  $\mathfrak{S}(\mathcal{H}_k)$  is the set of all density operators on  $\mathcal{H}_k$  ( $k = 1, 2$ ). Quantum channel  $\Lambda^*$  is a mapping from  $\mathfrak{S}(\mathcal{H}_1)$  to  $\mathfrak{S}(\mathcal{H}_2)$ .  $\Lambda^*$  is linear if  $\Lambda^*(\lambda\rho_1 + (1 - \lambda)\rho_2) = \lambda\Lambda^*(\rho_1) + (1 - \lambda)\Lambda^*(\rho_2)$  holds for any  $\rho_1, \rho_2 \in \mathfrak{S}(\mathcal{H}_1)$

and any  $\lambda \in [0, 1]$ .  $\Lambda^*$  is completely positive (C.P.) if  $\Lambda^*$  is linear and its dual  $\Lambda : \mathbf{B}(\mathcal{H}_2) \rightarrow \mathbf{B}(\mathcal{H}_1)$  satisfies

$$\sum_{i,j=1}^n A_i^* \Lambda(\bar{A}_i \bar{A}_j) A_j \geq 0$$

for any  $n \in \mathbf{N}$ , any  $\{\bar{A}_i\} \subset \mathbf{B}(\mathcal{H}_2)$  and any  $\{A_i\} \subset \mathbf{B}(\mathcal{H}_1)$ , where the dual map  $\Lambda$  of  $\Lambda^*$  is defined by

$$\text{tr} \Lambda^*(\rho) B = \text{tr} \rho \Lambda(B), \quad \forall \rho \in \mathfrak{S}(\mathcal{H}_1), \quad \forall B \in \mathbf{B}(\mathcal{H}_2). \quad (1.1)$$

Almost all physical transformation can be described by the CP channel [5], [7], [8]

Let  $\mathcal{K}_1$  and  $\mathcal{K}_2$  be two Hilbert spaces expressing noise and loss systems, respectively. Quantum communication process including the influence of noise and loss is denoted by the following scheme [6]: Let  $\rho$  be an input state in  $\mathfrak{S}(\mathcal{H}_1)$ ,  $\xi$  be a noise state in  $\mathfrak{S}(\mathcal{K}_1)$ .

$$\begin{array}{ccc} \mathfrak{S}(\mathcal{H}_1) & \xrightarrow{\Lambda^*} & \mathfrak{S}(\mathcal{H}_2) \\ \gamma^* \downarrow & & \uparrow a^* \\ \mathfrak{S}(\mathcal{H}_1 \otimes \mathcal{K}_1) & \xrightarrow{\Pi^*} & \mathfrak{S}(\mathcal{H}_2 \otimes \mathcal{K}_2) \end{array}$$

The above maps  $\gamma^*$ ,  $a^*$  are given as

$$\gamma^*(\rho) = \rho \otimes \xi, \quad \rho \in \mathfrak{S}(\mathcal{H}_1), \quad (1.2)$$

$$a^*(\sigma) = \text{tr}_{\mathcal{K}_2} \sigma, \quad \sigma \in \mathfrak{S}(\mathcal{H}_2 \otimes \mathcal{K}_2). \quad (1.3)$$

The map  $\Pi^*$  is a channel from  $\mathfrak{S}(\mathcal{H}_1 \otimes \mathcal{K}_1)$  to  $\mathfrak{S}(\mathcal{H}_2 \otimes \mathcal{K}_2)$  determined by physical properties of the device transmitting information. Hence the channel for the above process is given by

$$\Lambda^*(\rho) \equiv \text{tr}_{\mathcal{K}_2} \Pi^*(\rho \otimes \xi) = (a^* \circ \Pi^* \circ \gamma^*)(\rho) \quad (1.4)$$

for any  $\rho \in \mathfrak{S}(\mathcal{H}_1)$ . Based on this scheme, the noisy quantum channel [9] are constructed as follows:

Noisy quantum channel  $\Lambda^*$  with a noise state  $\xi$  is defined by

$$\Lambda^*(\rho) \equiv \text{tr}_{\mathcal{K}_2} \Pi^*(\rho \otimes \xi) = \text{tr}_{\mathcal{K}_2} V(\rho \otimes \xi) V^*, \quad (1.5)$$

where  $\xi = |m_1\rangle\langle m_1|$  is the  $m_1$  photon number state in  $\mathfrak{S}(\mathcal{K}_1)$  and  $V$  is a mapping from  $\mathcal{H}_1 \otimes \mathcal{K}_1$  to  $\mathcal{H}_2 \otimes \mathcal{K}_2$  denoted by

$$V(|n_1\rangle \otimes |m_1\rangle) = \sum_j^{n_1+m_1} C_j^{n_1, m_1} |j\rangle \otimes |n_1 + m_1 - j\rangle,$$

$$C_j^{n_1, m_1} = \sum_{r=L}^K (-1)^{n_1+j-r} \frac{\sqrt{n_1! m_1! j! (n_1 + m_1 - j)!}}{r! (n_1 - j)! (j - r)! (m_1 - j + r)!} \alpha^{m_1 - j + 2r} (-\bar{\beta})^{n_1 + j - 2r} \quad (1.6)$$

$K$  and  $L$  are constants given by  $K = \min\{n_1, j\}$ ,  $L = \max\{m_1 - j, 0\}$ . In particular for the coherent input state  $\rho = |\theta\rangle\langle\theta| \otimes |\kappa\rangle\langle\kappa| \in \mathfrak{S}(\mathcal{H}_1 \otimes \mathcal{K}_1)$ , we obtain the output state of  $\Pi^*$  by

$$\Pi^*(|\theta\rangle\langle\theta| \otimes |\kappa\rangle\langle\kappa|) = |\alpha\theta + \beta\kappa\rangle\langle\alpha\theta + \beta\kappa| \otimes |-\bar{\beta}\theta + \alpha\kappa\rangle\langle-\bar{\beta}\theta + \alpha\kappa|,$$

where  $\Pi^*$  is called a generalized beam splitting. When the noise  $\xi_0 = |0\rangle\langle 0|$  is given by the vacuum state,  $\Lambda_0^*$  is called an attenuation channel [5] and  $\mathcal{E}_0^*$  (or  $\Pi_0^*$ ) is called a beam splitting. Based on liftings, the beam splitting was studied by Accardi - Ohya [1] and Fichtner - Freudenberg - Libsher [2].

## 2. Quantum logical gate on symmetric Fock space

Recently, we reformulate a quantum channel for the FTM gate and we rigorously study the conservation of information for FTM gate [10]. However, it might be difficult to realize the photon number state  $|n\rangle\langle n|$  for the input of the Kerr medium physically.

In this section, we reformulate beam splittings on symmetric Fock space and we introduce a new operator on this space instead of the Kerr medium. We discuss the mathematical formulation of quantum logical gate by means of beam splittings and the new operator.

Let  $G$  be a complete separable metric space and  $\mathcal{G}$  be a Borel  $\sigma$ -algebra of  $G$ .  $\nu$  is called a locally finite diffuse measure on the measurable space  $(G, \mathcal{G})$  if  $\nu$  satisfies the conditions (1)  $\nu(K) < \infty$  for bounded  $K \in \mathcal{G}$  and (2)  $\nu(\{x\}) = 0$  for any  $x \in G$ . We denote the set of all finite integer - valued measures  $\varphi$  on  $(G, \mathcal{G})$  by  $M$ . For a set  $K \in \mathcal{G}$  and a natural number  $n \in \mathbb{N}$ , we put the set of  $\varphi$  satisfying  $\varphi(K) = n$  as

$$M_{K,n} \equiv \{\varphi \in M; \varphi(K) = n\}.$$

Let  $\mathfrak{M}$  be a  $\sigma$ -algebra generated by  $M_{K,n}$ .  $F$  is the  $\sigma$ -finite measure on  $(M, \mathfrak{M})$  defined by

$$F(Y) \equiv 1_Y(\varphi_0) + \sum_{n=1} \frac{1}{n!} \int_M 1_Y \left( \sum_{j=1}^n \delta_{x_j} \right) v^n(dx_1 \cdots dx_n),$$

where  $1_Y$  is the characteristic function of a set  $Y$ ,  $\varphi_0$  is an empty configuration in  $M$  and  $\delta_{x_j}$  is a Dirac measure in  $x_j$ .  $\mathcal{M} \equiv L^2(M, \mathfrak{M}, F)$  is called a (symmetric) Fock space. We define an exponential vector  $\exp_g : M \rightarrow \mathbb{C}$  generated by a given function  $g : G \rightarrow \mathbb{C}$  such that

$$\exp_g(\varphi) \equiv \begin{cases} 1 & (\varphi = \varphi_0), \\ \prod_{x \in \varphi} g(x) & (\varphi \neq \varphi_0), \end{cases} \quad (\varphi \in M).$$

### 2.1. Generalized beam splittings on Fock space

Let  $\alpha, \beta$  be measurable mappings from  $G$  to  $\mathbb{C}$  satisfying  $\bar{\alpha}$

$$|\alpha(x)|^2 + |\beta(x)|^2 = 1, \quad x \in G.$$

We introduce an unitary operator  $V_{\alpha,\beta} : \mathcal{M} \otimes \mathcal{M} \rightarrow \mathcal{M} \otimes \mathcal{M}$  defined by

$$\begin{aligned} (V_{\alpha,\beta}\Phi)(\varphi_1, \varphi_2) &\equiv \sum_{\hat{\varphi}_1 \leq \varphi_1} \sum_{\hat{\varphi}_2 \leq \varphi_2} \exp_{\alpha}(\hat{\varphi}_1) \exp_{\beta}(\varphi_1 - \hat{\varphi}_1) \exp_{-\bar{\beta}}(\hat{\varphi}_2) \exp_{\bar{\alpha}}(\varphi_2 - \hat{\varphi}_2) \\ &\quad \times \Phi(\hat{\varphi}_1 + \hat{\varphi}_2, \varphi_1 + \varphi_2 - \hat{\varphi}_1 - \hat{\varphi}_2) \end{aligned}$$

for  $\Phi \in \mathcal{M} \otimes \mathcal{M}$  and  $\varphi_1, \varphi_2 \in M$ . Let  $\mathcal{A} \equiv \mathbb{B}(\mathcal{H})$  be the set of all bounded operators on  $\mathcal{M}$  and  $\mathfrak{S}(\mathcal{A})$  be the set of all normal states on  $\mathcal{A}$ .  $\mathcal{E}_{\alpha,\beta} : \mathcal{A} \otimes \mathcal{A} \rightarrow \mathcal{A} \otimes \mathcal{A}$  defined by

$$\mathcal{E}_{\alpha,\beta}(C) \equiv V_{\alpha,\beta}^* C V_{\alpha,\beta}, \quad \forall C \in \mathcal{A} \otimes \mathcal{A}$$

is the lifting in the sense of Accardi and Ohya [1] and the dual map  $\mathcal{E}_{\alpha,\beta}^*$  of  $\mathcal{E}_{\alpha,\beta}$  given by

$$\mathcal{E}_{\alpha,\beta}^*(\omega)(\bullet) \equiv \omega(\mathcal{E}_{\alpha,\beta}(\bullet)), \quad \forall \omega \in \mathfrak{S}(\mathcal{A} \otimes \mathcal{A})$$

is the CP channel from  $\mathfrak{S}(\mathcal{A} \otimes \mathcal{A})$  to  $\mathfrak{S}(\mathcal{A} \otimes \mathcal{A})$ . Using the exponential vectors, one can denote a coherent state  $\theta^f$  by

$$\theta^f(A) \equiv \langle \exp_f, A \exp_f \rangle e^{-\|f\|^2}, \quad \forall f \in L^2(G, \nu), \quad \forall A \in \mathcal{A}.$$

In particular, for the input coherent states  $\eta_0 \otimes \omega_0 = \theta^f \otimes \theta^g$ , two output states  $\omega_1(\bullet) \equiv \eta_0 \otimes \omega_0(\mathcal{E}_{\alpha,\beta}((\bullet) \otimes I))$  and  $\eta_1(\bullet) \equiv \eta_0 \otimes \omega_0(\mathcal{E}_{\alpha,\beta}(I \otimes (\bullet)))$  are obtained by

$$\omega_1 = \theta^{\alpha f + \beta g}, \quad \eta_1 = \theta^{-\bar{\beta} f + \bar{\alpha} g}.$$

$\mathcal{E}_{\alpha,\beta}^*$  is called a generalized beam splitting on Fock space because it also hold the same properties satisfied by the generated beam splitting  $\Pi^*$  in Section 1.

Now we introduce a self-adjoint unitary operator  $\tilde{U}$ , which denotes a new device instead of the Kerr medium, defined by

$$\tilde{U}(\Phi)(\varphi_1, \varphi_2) \equiv (-1)^{|\varphi_1||\varphi_2|} \Phi(\varphi_1, \varphi_2)$$

for  $\Phi \in \mathcal{M} \otimes \mathcal{M}$  and  $\varphi_1, \varphi_2 \in G$ , where  $|\varphi_k| \equiv \varphi_k(G)$  ( $k = 1, 2$ ). For the input state  $\omega_1 \otimes \kappa \equiv \theta^f \otimes \frac{1}{\|\psi\|^2} \langle \psi, \bullet \psi \rangle$ , the output state  $\omega_2$  of new device is

$$\omega_2(A) \equiv \omega_1 \otimes \kappa(\tilde{U}(A \otimes I)\tilde{U}) = \frac{1}{\|\psi\|^2} \int_M F(d\varphi) |\psi(\varphi)|^2 \theta^{(-1)^{|\varphi|^2} f}(A)$$

for any  $A \in \mathcal{A}$ ,  $\psi \in \mathcal{M}$  ( $\psi \neq 0$ ) and  $f \in L^2(G, \nu)$ . If  $\kappa$  is given by the vacuum state  $\theta^0$ , then the output state  $\omega_2$  is equals to  $\omega_1$  and if  $\kappa$  is given by one particle state, that is,  $\kappa = \frac{1}{\|\psi\|^2} \langle \psi, \bullet \psi \rangle$  with  $\psi \upharpoonright_{M_1}$  (where  $M_1$  is the set of one-particle states), then  $\omega_2$  is obtained by  $\theta^{-f}$ . Let  $M_o$  (resp.  $M_e$ ) be the set of  $\varphi \in M$  which satisfies that  $|\varphi|$  is odd (resp. even) and  $M$  be the union of  $M_o$  and  $M_e$ . The output states  $\omega_2$  of the new device is written by

$$\omega_2(A) = \lambda_1 \theta^{-f}(A) + \lambda_2 \theta^f(A) \quad \forall A \in \mathcal{A},$$

where  $\lambda_1$  and  $\lambda_2$  are given by

$$\begin{cases} \lambda_1 = \frac{1}{\|\psi\|^2} \int_{M_o} F(d\varphi) |\psi(\varphi)|^2, \\ \lambda_2 = \frac{1}{\|\psi\|^2} \int_{M_e} F(d\varphi) |\psi(\varphi)|^2. \end{cases}$$

Two output states  $\omega_3(\bullet) \equiv \omega_2 \otimes \eta_2(\mathcal{E}_{\alpha_2, \beta_2}((\bullet) \otimes I))$  and  $\eta_3(\bullet) \equiv \omega_2 \otimes \eta_2(\mathcal{E}_{\alpha_2, \beta_2}(I \otimes (\bullet)))$  of the total logical gate including two beam splittings  $\mathcal{E}_{\alpha_k, \beta_k}^*$  with  $(|\alpha_k|^2 + |\beta_k|^2 = 1)$  ( $k = 1, 2$ ) and the new device instead of Kerr medium are obtained by

$$\begin{aligned} \omega_3 &= \lambda_1 \theta^{\alpha_2(-(\alpha_1 f + \beta_1 g)) + \beta_2(-\bar{\beta}_1 f + \bar{\alpha}_1 g)} + \lambda_2 \theta^{\alpha_2(\alpha_1 f + \beta_1 g) + \beta_2(-\bar{\beta}_1 f + \bar{\alpha}_1 g)}, \\ \eta_3 &= \lambda_1 \theta^{-\bar{\beta}_2(-(\alpha_1 f + \beta_1 g)) + \bar{\alpha}_2(-\bar{\beta}_1 f + \bar{\alpha}_1 g)} + \lambda_2 \theta^{-\bar{\beta}_2(\alpha_1 f + \beta_1 g) + \bar{\alpha}_2(-\bar{\beta}_1 f + \bar{\alpha}_1 g)}, \end{aligned}$$

where  $\omega_2 = \lambda_1 \theta^{-(\alpha_1 f + \beta_1 g)} + \lambda_2 \theta^{\alpha_1 f + \beta_1 g}$  and  $\eta_2 = \eta_1 = \theta^{-\beta_1 f + \alpha_1 g}$ .

Based on the above settings, we could show that new logical gate performs the complete truth table. The further development of our study will be appear in [11].

## References

- [1] L. Accardi and M. Ohya, Compound channels, transition expectations, and liftings, *Appl. Math. Optim.* Vol.39, 33-59, 1999.
- [2] K.H. Fichtner, W. Freudenberg and V. Liebscher, Beam splittings and time evolutions of Boson systems, *Fakultät für Mathematik und Informatik, Math/ Inf/96/ 39*, Jena, 105, 1996.
- [3] E. Fredkin and T. Toffoli, Conservative logic, *International Journal of Theoretical Physics* , **21** , pp. 219-253 1982.
- [4] G.J. Milburn, Quantum optical Fredkin gate, *Physical Review Letters* , **62**, 2124-2127, 1989.
- [5] M. Ohya, Quantum ergodic channels in operator algebras, *J. Math. Anal. Appl.* **84**, pp. 318 - 327, 1981.
- [6] M. Ohya, On compound state and mutual information in quantum information theory, *IEEE Trans. Information Theory*, **29**, pp. 770 - 777, 1983.
- [7] M. Ohya, Some aspects of quantum information theory and their applications to irreversible processes, *Rep. Math. Phys.*, **27**, pp. 19 - 47, 1989.
- [8] M. Ohya and D. Petz, *Quantum Entropy and Its Use*, Springer, 1993.
- [9] M. Ohya and N. Watanabe, Construction and analysis of a mathematical model in quantum communication processes, *Electronics and Communications in Japan, Part 1*, Vol.68, No.2, 29-34, 1985.
- [10] M. Ohya and N. Watanabe, On mathematical treatment of optical Fredkin - Toffoli - Milburn gate, *Physica D*, Vol.120, 206-213, 1998.
- [11] W. Freudenberg, M. Ohya and N. Watanabe, Generalized Fock space approach to Fredkin - Toffoli - Milburn gate, *SUT preprint*.